

auxiliary switch AX, EasyPact EZC100, EasyPact CVS 100BS, 1 common point changeover contact

EZAUX10

Main

Range of product	EZC100	
Range	EasyPact	
Device short name	AX	
Product or component type	Switch	
Device application	Signalling	
Range compatibility	EasyPact EZC circuit breaker	
Signal contacts composition	1 NO/NC	

Complementary

Auxiliary contacts type	Standard
[Ith] conventional free air thermal current	5 A
[le] rated operational current	AC-12: 3 A at 250 V AC 50/60 Hz
	AC-12: 5 A at 125 V AC 50/60 Hz
	AC-12: 5 A at 24 V AC 50/60 Hz
	AC-12: 5 A at 48 V AC 50/60 Hz
	AC-15: 2 A at 250 V AC 50/60 Hz
	AC-15: 3 A at 125 V AC 50/60 Hz
	AC-15: 5 A at 24 V AC 50/60 Hz
	AC-15: 5 A at 48 V AC 50/60 Hz
	DC-12: 0.2 A at 250 V DC
	DC-12: 0.4 A at 125 V DC
	DC-12: 2.5 A at 48 V DC
	DC-12: 4 A at 24 V DC
	DC-14: 0.2 A at 250 V DC
	DC-14: 0.4 A at 125 V DC
	DC-14: 1 A at 48 V DC
	DC-14: 3 A at 24 V DC
Minimum load	10 mA at 24 V
Auxiliary connection terminal	Lead wire

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2.5 cm
Package 1 Width	7.0 cm
Package 1 Length	8.5 cm
Package 1 Weight	40.0 g

Contractual warranty

Warranty

18 months



Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing "Use Better, Use Longer, Use Again" campaign to extend product lifetimes and recyclability.

Environmental Data explained >

How we assess product sustainability >

Use Better

WEEE

EU RoHS Directive	Compliant	
REACh Regulation	REACh Declaration	
Use Again		
○ Repack and remanufacture		
Take-back	No	

The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins