

sanwa®

TOKYO JAPAN

DIGITAL EARTH TESTER

PDR4000

On Sale Soon



APPLICATIONS AND FEATURES

- Measures earth resistance in three ranges : 40Ω, 400Ω, 4000Ω.
- Capable of measuring earth voltage.
- 3 ¾ digit (4000 counts).
- LCD backlight display.
- 2mA measuring current permits the testing of earth resistance without tripping earth leakage current breakers in the circuit under test.
- Data hold function.
- Relative function.
- Auto power-off function.
- Low battery indication.

SPECIFICATIONS

	Measuring range	Accuracy
Earth resistance measuring ranges	Earth Resistance : 0~40Ω / 0~400Ω / 0~4000Ω Earth Voltage : 0~400V (40~500Hz)	Earth Resistance ±(2%rdg+3dgt) Earth Voltage ±(2%rdg+3dgt)
Earth resistance resolution	0~40Ω : 0.01Ω 0~400Ω : 0.1Ω 0~4000Ω : 1Ω	
Measuring system	Earth resistance by constant current inverter 820 Hz, 2mA approx.	
Size / Mass	163(L) x 102(W) x 50(D)mm / Approx. 440g (battery included)	
Battery	1.5V (AA) x 6	
Standard accessories included	Test lead set , Auxiliary earth spikes , Manual , Batteries	



Specifications and external appearance of the product described above may be revised for modification without prior notice.

sanwa®

SANWA ELECTRIC INSTRUMENT CO., LTD.

Dempa Bldg, 4-4 Sotokanda 2-Chome, Chiyoda-Ku, Tokyo 101-0021 Japan
Tel:+81-3-3251-0941 Fax:+81-3-3256-9740

www.sanwa-meter.co.jp

Distributed by